

Part Number: 5961003801

61 TOROID

Explanation of Part Numbers:

- Digits 1 & 2 = Product Class
- Digits 3 & 4 = Material Grade
- 9th digit 1 = Parylene Coating, 2 = Thermo-Set Plastic Coating

**A ring configuration provides the ultimate utilization of the intrinsic ferrite material properties. Toroidal cores are used in a wide variety of applications such as power input filters, ground-fault interrupters, common-mode filters and in pulse and broadband transformers.**

All toroidal cores are supplied burnished to break sharp edges.

Coating Options:

- Toroids with an outside diameter of 9.5 mm (0.375") or smaller can be supplied Parylene C coated. The Parylene coating will increase the "A" and "C" dimensions and decrease the "B" dimension a maximum of 0.038 mm (0.0015"). The ninth digit of a Parylene coated toroid part number is a "1". See reference tables for the material characteristics of Parylene C. Parylene C coating is RoHS compliant.
- Toroids with an outside diameter of 9.5 mm (0.375") or larger can be supplied with a uniform coating of thermo-set plastic coating. This coating will increase the "A" and "C" dimensions and decrease the "B" dimension a maximum of 0.5 mm (0.020"). The 9th digit of the thermo-set plastic coated toroid part number is a "2". Thermo-set plastic coating is RoHS compliant.
- Thermo-set plastic coated parts can withstand a minimum breakdown voltage of 1000 Vrms, uniformly applied across the "C" dimension of the toroid.

**For any toroidal core requirement not listed in the catalog, please contact our customer service department for availability and pricing.**

[Catalog Drawing](#)  
[3D Model](#)

The C dimension may be modified to suit specific applications.

Weight: 106 (g)

| Dim | mm    | mm tol     | nominal inch | inch misc. |
|-----|-------|------------|--------------|------------|
| A   | 61    | $\pm 1.30$ | 2.4          | _          |
| B   | 35.55 | $\pm 0.85$ | 1.4          | _          |
| C   | 12.7  | $\pm 0.50$ | 0.5          | _          |

**Chart Legend**

$\Sigma l/A$  : Core Constant,  $l_e$  : Effective Path Length,  $A_e$  : Effective Cross-Sectional Area,  $V_e$  : Effective Core Volume

$A_L$  : Inductance Factor 

| Electrical Properties            |               |
|----------------------------------|---------------|
| $A_L$ (nH)                       | 170 $\pm$ 25% |
| $A_e$ (cm <sup>2</sup> )         | 1.58          |
| $\Sigma l/A$ (cm <sup>-1</sup> ) | 9.2           |
| $l_e$ (cm)                       | 14.5          |
| $V_e$ (cm <sup>3</sup> )         | 22.8          |

Toroids are tested for  $A_L$  values at 10 kHz.

Fair-Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288  
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • ferrites@fair-rite.com • www.fair-rite.com