

EMI Suppression Beads

(2643000201)

Part Number: 2643000201

43 SHIELD BEAD

Explanation of Part Numbers:

- Digits 1 & 2 = Product Class
- Digits 3 & 4 = Material Grade
- Last digit 1= Not Burnished 2 = Burnished
- The last digit of the Parylene coated part is a "4," which is available upon request. The minimum coating thickness beads is 0.005 mm (0.0002").

Fair-Rite offers a broad selection of ferrite EMI suppression beads with guaranteed minimum impedance specifications.

Our "Shield Bead Kit" (part number 0199000019) contains a selection of these beads.

For any EMI suppression bead requirement not listed here, feel free to contact our customer service for availability and pricing.

[Catalog Drawing](#)

[3D Model](#)

The C dimension, the bead length, can be modified to suit specific applications.

Weight: 0.03 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	2	-0.15	0.076	-
B	1.05	+0.10	0.043	-
C	3.8	±0.25	0.15	-

Chart Legend

+ Test frequency

- The column "H (Oe)" gives for each bead the calculated dc bias field in oersted for 1 turn and 1 ampere direct current. The actual dc H field in the application is this value of "H" times the actual NI (ampere-turn) product. For the effect of the dc bias on the impedance of the bead material, see

figures 18-23 in the application note [How to choose Ferrite Components for EMI Suppression](#).

Typical Impedance (Ω)	
10 MHz	11.5
25 MHz ⁺	17.5
100 MHz ⁺	28
250 MHz	37


Electrical Properties	
H(Oe)	2.8

Suppression beads are controlled for impedances only. Minimum impedance values are specified for the + marked frequencies. The minimum impedance is typically the listed impedance less 20%.

[Catalog Drawing](#)

Single turn impedance tests for 73 and 43 material beads are performed on the E4990A Impedance Analyzer. The 61 material beads are tested on the E4991A / HP4291B Impedance Analyzer. Beads are tested with the shortest practical wire length.

Typical Impedance (Ω)	
10 MHz	12
25 MHz ⁺	16
100 MHz ⁺	31
250 MHz	46



[CSV Download](#)

